

KMG 5.1



1 x Remote

7 Input modes
6 Programmable Sound experience
Volume Control , Mic Volume
Sub Woofer Volume Control
Center Speaker Volume Control
Echo Effects Volume Control
138 x 45 x 16 mm
2 x AA Battery




2 x Wireless Microphone

LCD Display , Battery Indicator/ Frequency Indicator
Frequency: 740–790Mhz UHF
Dynamic Range: 100dB
THD (Total Harmonic Distortion) : <5% (1kHz, 1 W)
Working Range: 50m (Without obstacles)
Battery Life: 8 Hrs
Battery: 2 x 1.5AA
Frequency Learning VIA RF



5 x Starlet Satellite Speakers

THD (Total Harmonic Distortion) : <5% (1kHz, 1 W)
Power : 40W
5 Satellite Speakers
2x 2.5" Driver tweeter
Sensitivity 88dB
Frequency Response: 300Hz–20KHz
High graded Polymer ABS Plastic, Aluminium Grill
Matte Black Finish
61 x 83 x 123 mm | 0.5kg
**Wall Mount Bracket | Floor Stand



1 x 10" Bass Module

THD (Total Harmonic Distortion) : <5% (1kHz, 1 W)
Maximum Power : 100W
1 x 10" Driver
Sensitivity : 84dB
Frequency Responds: 37-500Hz
Side Ported Passive Woofer
328 x 363 x 340 mm | 12Kg
** Wall Bracket | Floor Mount

1 x Main Module



60W x 5 | 120W x 1 Woofer
3 x HDMI Input | 2.0 | HDCP 2.2 |
4K Pass-Thru (ARC)
Bluetooth 4.2 (SBC and AAC decoder support)
1 x USB (Calibration) | 1 x RCA Input
1 x Coaxial | 1 x TOSLink
2 x 1/4" Mic Input
15 band Parametric Equaliser for Music input,
15 band Parametric Equaliser for Microphone (Individual) input.
15 band Parametric Equaliser for Left/Right/ Center Speaker
15 band Parametric Equaliser for Surround Left/Right Speaker
15 band Parametric Equaliser for Surround Back Left/Right Speaker
5 band Parametric EQ for Echo and Reverb.
Precise Time delay for Reverb and Echo function
6 band Parametric EQ for Bass Module
Individual Gain Control for 7 Input Source
437x300 x 80mm | 4.5Kg

Package Size: 495 x 426 x 480 | 22kg | FCL20: 240 | FCL40: 500

Find out more setup information and Detailed information at www.thunderstone.technology

4K **dts** **DOLBY** **Bluetooth** **HDMI** **MAXXAUDIO**



Mounting systems (Optional)

KMG-B1 is supplied in box. Other bracket accessories are optional items by Bose
KMG3.1 Basic wiring and installation \$380, KMG 7.1 Basic wiring and installation \$580



KMG-B2 \$15/pc
KMG-SS1 \$29/pc
KMG-LS1 \$59/pc